

# HP LaserJet 1010/1012/1015 printer



The HP LaserJet 1010 series printer is a compact, reliable and easy-to-use personal printer, ideal for creating high quality documents. HP's instant-on fuser lets you print your first page in less than 10 seconds with print speeds up to 14 ppm.

**The ideal entry level LaserJet printer for professionals needing a cost-efficient, space-saving and reliable monochrome printer to produce a range of high quality black and white documents quickly and easily at home or in the office.**

**The affordable choice for the value-conscious user who wants professional quality documents.**

- This printer is an excellent choice for any business on a budget as it includes a high value HP LaserJet All-in-One print cartridge enabling you to produce professional quality documents economically.
- Achieve precise details, clear text and smooth greyscales from the first page to the last with up to 1200 dpi effective output quality using HP Resolution Enhancement technology.
- Enjoy flexible media handling with the horizontal 150-sheet input tray and the multipurpose priority feed slot.

**Get great results and save space with the smallest HP LaserJet ever.**

- Its exceptionally small size means it fits easily on a desk, shelf or other convenient space.
- Produce your documents quickly with fast print speeds of up to 14 ppm.
- No tedious wait for your print job as HP's instant-on fuser ensures the first page prints in less than ten seconds.
- With up to 16 MB of RAM (available with HP LaserJet 1015 printer) large print jobs are no problem.
- It supports host-based and PCL 5e printing (available with HP LaserJet 1015 printer).

**Simple to install and use, this plug-and-play HP LaserJet printer is ideal for worry-free printing.**

- Get going without delay as the set-up and installation process is straightforward.
- The All-in-One print cartridge design makes installation both simple and convenient, as it is intuitive to replace.
- Standard USB connectivity and parallel connectivity (available with HP LaserJet 1015 printer) ensures installation is easy.
- The printer has a simple user interface and you can check status and change configuration with Toolbox.
- Compatible with Windows® 95, 98, Me, 2000 and XP and Mac OS 9, OS X.



HP LaserJet 1015 printer



HP LaserJet 1012 printer



HP LaserJet 1010 printer

# HP LaserJet 1010/1012/1015 printer



## Technical specifications

|  |  |  |   |
|--|--|--|---|
| <b>Print technology</b>                | Monochrome Laser   |  |   |
| <b>Print speed</b>                     | HP LaserJet 1012/1015 printer: Up to 14 ppm; HP LaserJet 1010 printer: Up to 12 ppm<br>First page out: 10 sec. Instant-on fuser technology for no warm-up time – from warm or cold start.<br>(Exact speed varies depending on the system configuration, software program, and document complexity)   |  |   |
| <b>Processor</b>                       | 133 MHz, RISC processor  |  |   |
| <b>Memory</b>                          | HP LaserJet 1015 printer: 16 MB; HP LaserJet 1010/1012 printer: 8 MB   |  |   |
| <b>Print quality</b>                   | HP LaserJet 1012/1015 printer: 1200 dpi effective output (optical 600 x 600 dpi with HP Resolution Enhancement Technology REI and FastRes); HP LaserJet 1010 printer: 600 x 600 dpi with HP Resolution Enhancement technology (REI)  |  |   |
| <b>Printer languages</b>               | HP LaserJet 1015 printer: HP PCL 5e or host-based printing driver; HP LaserJet 1010/1012 printer: host-based   |  |   |
| <b>Economical printing</b>             | Economode (saves up to 50% toner), immediate return to save power mode after each print job due to instant-on fuser technology (saves electricity), N-up printing and manual duplex (saves paper)  |  |   |
| <b>Typefaces/fonts</b>                 | HP LaserJet 1015 printer: 26 built-in  |  |   |
| <b>Duty cycle</b>                      | HP LaserJet 1015 printer: up to 7,000 pages per month; HP LaserJet 1010/1012 printer: up to 5,000 pages per month  |  |   |
| <b>Print margins (A4)</b>              | Top: 4 mm, bottom: 4 mm, left: 4 mm, right: 4 mm   |  |   |
| <b>Media handling</b>                  | <b>Input</b>   | <b>Capacity</b>                                      | <b>Weight</b>                               |
|  | Main input tray  | Up to 150 sheets,<br>10 envelopes                    | 60 g/m <sup>2</sup> to 105 g/m <sup>2</sup> |
|  | <b>Output:</b>   | Sheets: up to 125, envelopes: 15, transparencies: 10 |   |
|  | <b>Duplex printing:</b>  | Manual   |   |
| <b>Media types</b>                     | Plain paper, envelopes, transparencies, card stock, postcards, labels  |  |   |
| <b>Paper handling</b>                  | LJ1015: 150-sheet main input tray, 10-sheet priority input tray; LJ1010, LJ1012: 150-sheet main input tray, 1-sheet priority input tray  |  |   |
| <b>Interface and connectivity</b>      | HP LaserJet 1015 printer: Two hot ports: USB compatible with the USB 2.0 specification, IEEE 1284-compliant bi-directional parallel<br>HP LaserJet 1010/1012 printer: USB compatible with the USB 2.0 specification<br>Optional: HP LaserJet 1015 printer: HP Jetdirect external print servers for Fast Ethernet (10/100Base-TX), Ethernet (10Base-T), Token Ring; HP wireless print servers for 802.11b Ethernet  |  |   |
| <b>Operating systems compatibility</b> | HP LaserJet 1015 printer: Microsoft® Windows® 98, Me, 2000, XP; Windows 95, NT 4.0 (SP3); Microsoft Windows XP 32-bit (print driver only); Mac OS 9, v 9.1 and higher, Mac OS X v 10.1, 10.2; MS-DOS. Latest drivers available from <a href="http://www.hp.com">http://www.hp.com</a><br>HP LaserJet 1010/1012 printer: Microsoft® Windows® 98, Me, 2000, XP; Microsoft Windows XP 32-bit  |  |   |
| <b>Minimum system requirements</b>     | Operating system requirements as recommended by the operating system vendor plus free hard disk space (140 MB for full installation, 10 MB for print drivers only); CD-ROM disk drive; USB, dedicated IEEE-1284 compliant bi-directional parallel, or ECP-compliant parallel port  |  |   |
| <b>Standard software</b>               | HP LaserJet 1015 printer: HP printer software on CD-ROM includes HP installer/uninstaller, HP PCL 5e and host-based drivers, HP toolbox for diagnostic status and configuration, help, documentation; HP LaserJet 1010/1012 printer: HP printer software on CD-ROM includes HP installer/uninstaller, host-based driver, HP toolbox for diagnostic status and configuration, help, documentation   |  |   |
| <b>Control panel</b>                   | Simplified control panel with "Go" and "Cancel job" buttons, and three LEDs for status   |  |   |
| <b>Power requirements</b>              | 110 to 127 VAC (± 10%), 50/60 Hz (± 2 Hz); 220 to 240 VAC (± 10%), 50/60 Hz (± 2 Hz)   |  |   |
| <b>Power Consumption</b>               | 0 watts maximum (off), 7 watts maximum (Powersave/standby), 214 watts maximum (printing)   |  |   |
| <b>Dimensions (w x d x h)</b>          | Out of package: 370 x 230 x 208 mm; packaged: 500 x 300 x 345 mm   |  |   |
| <b>Weight</b>                          | Out of package: 5.9 kg; packaged: 7.41 kg  |  |   |
| <b>Printer management</b>              | HP toolbox   |  |   |
| <b>Operating environment</b>           | Environmental ranges: Operating temperature: 10 to 32.5° C, recommended operating temperature: 10 to 32.5° C; operating humidity: 20 to 80% RH, recommended operating humidity: 20 to 80% RH; storage temperature: 0 to 40° C, storage humidity: 10 to 80% RH, noise level per ISO 9296: Sound power: LwAd: HP LaserJet 1010 printer: 6.2 B(A) (printing at 12 ppm), HP LaserJet 1012/1015 printer: 6.2 B(A) (printing at 14 ppm), sound pressure: LpAm 57 dB(A) – operator position, 48 dB(A) – bystander           |  |   |
| <b>Certifications</b>                  | Technical Regulations: Carries CE marking for EU & EFTA countries (Compliant to Low Voltage Directive 73/23/EEC / EMC Directive 89/336/EEC / R&TE Directive 1999/5/EC, Class 1 Laser/LED). For additional details, see Declaration of Conformity. Further compliance is given for: USA FCC/UL, Russia GOST, Poland B-Mark, Czech Republic (CSN *), Estonia (EEI *), Hungary (MEEI *), Lithuania (LS *), Slovakia (STN *), Slovenia (SQI *), South Africa (SASB *) and more. (* = IEC 60950, IEC 60825). Energy Star® |  |   |
| <b>Warranty</b>                        | 1 year standard bench repair and return (HP/dealer). Upgrade standard warranty with optional HP Care Pack services to 3 years (not included).  |  |   |

## Ordering information

|               |  |
|---------------|--|
| <b>Q2460A</b> | HP LaserJet 1010 printer, HP print cartridge (in protective bag), getting started guide, software and electronic user guide on CD-ROM, power cord, printer media input tray, printer priority input tray |
| <b>Q2461A</b> | HP LaserJet 1012 printer, as above   |
| <b>Q2462A</b> | HP LaserJet 1015 printer, as above plus input tray cover   |

### Supplies

|               |  |
|---------------|--|
| <b>Q2612A</b> | HP Ultraprecise Standard Capacity Print Cartridge, black (up to 2,000 pages**) |
|---------------|--|

### Cables

|               |                                       |
|---------------|---------------------------------------|
| <b>C6518A</b> | HP USB cable – 2 m                    |
| <b>C2950A</b> | HP IEEE parallel cable (B-type), 2 m* |
| <b>C2951A</b> | HP IEEE parallel cable (B-type), 3 m* |

### HP Jetdirect print servers\*

|                 |   |
|-----------------|---|
| <b>J3258B</b>   | HP Jetdirect 170x external print server (parallel, 10/100Base-T)  |
| <b>J6035B</b>   | HP Jetdirect 175x external print server (USB, 10/100Base-TX)      |
| <b>J3263A</b>   | HP Jetdirect 300x external print server (parallel, 10/100Base-TX) |
| <b>J6038A</b>   | HP Jetdirect 310x external print server (USB, 10/100Base-TX)      |
| <b>J6061A</b>   | HP Jetdirect 380x wireless external print server (USB – 802.11b)  |
| <b>J6062A</b>   | HP WP110 wireless external print server (parallel – 802.11b)      |
| <b>MPIPA130</b> | Bluetooth Print Adapter, Europe (parallel – Bluetooth)            |

### Service & support

|                 |   |
|-----------------|---|
| <b>U6489A/E</b> | HP Care Pack, return to HP, 3 years<br>*Only compatible with the HP LaserJet 1015 printer<br>**based on 5% coverage |
|-----------------|---|



<http://www.hp.com>

For more information, please call your local HP sales office or representative: **Austria:** 0800 242 242, **Algeria:** (0)61 56 45 43, **Bahrain:** 800 728, **Belgium:** (078) 15 20 30 (0.0496 EUR/min), **Bulgaria:** (+359) 2960 1940, **Croatia:** (+385 1) 60 60 200, **Czech Republic:** (00 420 2) 261 108 108 (Prague), **Denmark:** 45991700 or 70101125, **Egypt:** 532 5222, **Estonia:** (+372) 6813 823, **Finland:** (+358) 0205350 or 0205 350, **France:** (1) 69 82 6060, **Germany:** 0180 532 6222 (12 Cent/min), **Greece:** (01) 678 96 00, **Hungary:** (+36) 1 382-1111, **Iceland:** (354) 570 1000, **Ireland:** + 353 1 6158200, **Israel:** (972) 9 8304848, **Italy:** (02) 92121, **Kazakhstan:** +7 (3272) 980 824, **Latvia:** (371) 800 80 12, **Lithuania:** 8 800 10000 or 8 5 2103333, **Luxembourg:** (+352) 263 160 34, **Middle East:** 00971 4 883 4427, **Morocco (African Region):** +212 22 40 47 47, **Netherlands:** (020) 5476666, **Norway:** 22 735600, **Poland:** infolinia: 0-800 122 622, **Portugal:** (808) 206 001, **Romania:** (+401) 205 3300, **Russia:** +7 (095) 797 35 00, **Saudi Arabia:** 800 124 4646, **Serbia/Montenegro:** +381 11 334 21 02, **Slovakia:** +421-2-50222111, **Slovenia:** +3861 2307 420, **South Africa:** 0800 118 883, **Spain:** (91) 634 88 00, **Sweden:** (08) 444 2000, **Switzerland:** 0848 88 44 66, **Tunisia:** 71 891 222, **Turkey:** +90 (216) 579 71 71, **UAE:** 8004910, **UK:** 08705 474747, **Ukraine:** +380 44 490 61 20.

The information contained in this document is subject to change without notice. All other products mentioned herein may be trademarks of their respective companies. Microsoft, Windows and MS Windows are U.S. registered trademarks of Microsoft Corporation.

© Copyright Hewlett-Packard 2003  
Created in the EU 08/03  
5981-9158EEE